



Brief Description

- Mini BTE noiser, also for use in tinnitus retraining therapy
- Automatic presetting (First Fit) of frequency-dependent noise level on the basis of pure tone audiometry data in order to realize an audible broadband signal
- White/pink noise can be selected
- 4-channel noise formation
- 3 programmable crossover frequencies
- Low and high frequency tone controls can be separately programmed
- Programmable volume control (control range: 32, 16, 8 dB, off)
- Printing on case: WAVE VC

Max. output noise level

80

Description

Fitting: Personal Computer (PC, notebook)
Channels: 4
No. of programs: 2
No. of microphones: 0
VC: yes
Program pushbutton: no (021-switch)

Options

Accessories

HADEO care range,
eyeglass-adapter

Homologation Approval Germany

- **Applicable standards**
Ear simulator measurement: EN 60118-0
2 cc coupler measurement: EN 60118-7


- **Measuring settings**
If not mentioned differently in the individual diagrams, the following adjustments are effective:
Trimmer settings: max
Full on Gain (CONNEXX Test setting)

Technical Specifications


Ear Simulator	Maximum output noise level [dB]	2 cc Coupler
90		80
Battery Type		
13		13
Battery current [mA]		
0,65	typical	0,65

Ear Simulator


Max. output noise level



Max. output noise level and effect of NH




Max. output noise level and effect of NL




2 cc Coupler

Max. output noise level



Max. output noise level and effect of NH



Max. output noise level and effect of NL

